



Getting started		
Setting up your voicemail	Making calls to	
From your office phone:	Phones in your office*	Extension Dialing (2-7 digits+#)
 Press the Voicemail button. When prompted, enter the temporary passcode + # (provided in your welcome email). Follow the automated prompts to record your name, set your schedule, and record an "open" and "closed" greeting. From outside of the office: Dial the voicemail retrieval number (provided in your welcome email). 	Phones in other offices	10-digit phone number
	Local	10-digit phone number
	Long Distance	10-digit phone number
	Toll-Free	10-digit phone number
	International	011 + country code + city code + number
	Operator*	0
2. When prompted, enter your 10-digit phone number + #.	Information**	411
 Reenter your 10-digit phone number + #. Follow automated prompts to record your name, set your 	TTY	711
Schedule, and record an "Open" and "Closed" greeting.	Emergency Services***	911
Voicemail PIN guidelines		
PINs are required (can no longer be skipped) PINs must be 6-15 numeric digits in length The PIN cannot solely consist of your telephone number or any part of your telephone number The same digit cannot be repeated more than twice: Allowed examples: 11xxxx, xxx88xxx, xxxxx99 Not allowed examples: 222xxx, xx444xx, 77777 The entire PIN cannot be sequential, either ascending or descending: Allowed examples: 012347, 98761, 01234560 Not allowed examples: 123456, 0123456789, 9876543210	 * When dialing extensions or numbers less than 10 digits, add a # after the number to make the call go through faster. ** Information may be restricted on some phones, charges may apply. *** Emergency services are tied to the service address of your phone. 	
Phone features Consultative transfer	Blind transfer	
 Consultative transfer allows you to announce the call prior to completing the transfer process: 1. While on a call, tap the Transfer soft key. The person you're talking to is placed on hold and you receive dial tone. 2. Dial the extension+# or 10-digit number for the individual you wish to transfer to. 3. After announcing the call, tap the Transfer soft key or hang up to complete the transfer. 4. If the party does not answer or chooses not to accept the transfer, tap the Cancel soft key to stop the transfer process and return to the caller. 	 Blind transfer does not allow you to announce the caller: 1. While on a call, tap the Transfer soft key. The person you're talking to is placed on hold and you hear dial tone. 2. Tap the Blind** icon (upper right on the display). 3. Enter the extension+# or 10-digit number for the individual you wish to transfer to. 4. The blind transfer is complete. 5. If you make a mistake or change your mind, tap the Back Arrow icon in the upper left corner of the display, to return to the caller. This must be done before the # or 10th digit of a 10-digit number is entered. **If Blind transfer is your default transfer type, you'll tap the Consultative icon to perform a consultative transfer which overrides blind transfer. Note: When transferring in this manner, the caller ID that appears to the recipient of the transfer is the caller ID of the incoming caller. 	
recipient of the transfer, after the transfer is complete, is the caller ID of the calling party.		
Transferring a call to voicemail	Making a conference	
 To transfer callers directly to voicemail: While on a call, tap the To Vmail soft key. Note that the caller will still be on your line and will be able to hear should you speak. Dial the recipient's extension and tap the Enter soft key. The call releases from your phone and transfers directly to that individual's voicemail. To cancel the transfer process, tap the Cancel soft key to return to the caller. 	talking to is placed on hDial the number of the pAfter announcing the co- complete the conferenceIf they don't answer or configuration	Conference soft key. The person you're old and you receive dial tone. person you want to add to your call. Inference, tap the Conference soft key to

Note: When transferring in this manner, the caller ID that registers in the recipient's voicemail is the caller ID of the incoming caller.





Phone features, continued	
Forwarding calls	Call park
 Forward your calls to another extension or outside number: To enable forwarding: Tap the Forward soft key. Tap the option you want to enable: Always, No Answer, or Busy. On the keypad, enter the number or extension you want to forward to, then tap the Enable soft key. An arrow icon appears next to your extension confirming activation of forwarding. To disable forwarding: To disable, tap the Forward soft key, then tap the forwarding option you wish to disable. Tap the Disable soft key to remove forwarding. 	 Call park allows you to place calls on hold, then retrieve from another phone within your office: To park a call: To park a call: To park the call against your extension, simply press the # key, or enter any extension+#. The call is parked on that extension. To retrieve a parked call: At dial tone, tap the Retrieve soft key. When prompted, enter the extension+# the call was parked on.
Do not disturb (DND)	Using call logs
 Do Not Disturb (DND) sends callers directly to voicemail. To activate DND: Tap the DND soft key. An icon appears next to your extension confirming activation of DND. To deactivate DND: Tap the DND soft key again. The icon no longer displays confirming deactivation of DND. 	Your phone retains a list of call logs that you can access by tapping the Callers soft key. You can also access call logs by pressing the Home button, then tap the Directories icon on the color touch screen. All call logs retain records for 100 days. You can also access more detailed call logs from your Outlook toolbar and using the VoIP portal: <u>https://voip.centurylink.com/</u>
Speed dial 8	Speed dial 100
 Speed dial 8 allows you to program up to 8 contacts using 1-digit codes 2 through 9. 1. With dial tone, dial *74. When prompted, enter the 1-digit code you'd like to program, followed by a 10-digit phone number. 2. To use speed dial 8, while the phone is on-hook (no dial tone), dial a 1-digit code on the keypad, then lift the handset or press the handsfree button. Example: Do not establish dial tone, dial "x", then lift the handset; x = the 1-digit code you want to dial. 	 Speed dial 100 allows you to program up to 100 contacts using 2-digit codes 00 through 99. 1. With dial tone, dial *75. When prompted, enter the 2-digit code you'd like to program, followed by the 10-digit phone number. 2. To use speed dial 100, while the phone is on-hook (no dial tone), enter # + 2-digit code, then lift the handset or press the handsfree button. Example: Do not establish dial tone, dial #+xx and lift the handset; xx = the 2-digit code you want to dial.

Voicemail

Retrieving voicemail (3 ways to access)	Voicemail shortcuts	
 From your office phone: Press the Voicemail key. When prompted, enter your passcode + #. From outside the office*: Dial the voicemail retrieval number. When prompted, enter your 10-digit phone number + #. When prompted, enter your passcode + #. By calling your direct-dial number: During your greeting, press 7. 	To get your messages1,1To listen to your messages4To repeat menu5To hear message details again6To send copy of message7To delete message8To reply to message8,8To place a call to this	While a message is playing3,3,7Delete message without listening to it1Rewind message (10 sec)1,1Restart message from body2Pause/resume3Fast forward (10 sec)3,3End of message
 When prompted, enter your passcode + #. Note: *You can save a contact in your mobile phone to automatically log you in by adding a contact with the voicemail retrieval phone number <pause> [10-digit number] # <pause> [password] #.</pause></pause> 	person 9 To save this message	4 Slow message down

VoIP portal	
Login information	New VoIP portal password
URL: <u>https://voip.centurylink.com</u> (make this link a favorite)	Record your password here:
Username: included in the welcome email from your administrator.	
Password: included in the welcome email from your administrator.	